

A Service of

**PRIII** 

Leibniz-Informationszentrum Wirtschaft Leibniz Information Centre for Economics

Sato, Mitsuhide et al.

# **Article**

# Increasing the efficiency of a drone motor by arranging magnetic sheets to windings

Energy Reports

# **Provided in Cooperation with:** Elsevier

*Suggested Citation:* Sato, Mitsuhide et al. (2020) : Increasing the efficiency of a drone motor by arranging magnetic sheets to windings, Energy Reports, ISSN 2352-4847, Elsevier, Amsterdam, Vol. 6, Iss. 2, pp. 439-446, [https://doi.org/10.1016/j.egyr.2019.11.100](https://doi.org/10.1016/j.egyr.2019.11.100%0A)

This Version is available at: <https://hdl.handle.net/10419/243914>

# **Standard-Nutzungsbedingungen:**

Die Dokumente auf EconStor dürfen zu eigenen wissenschaftlichen Zwecken und zum Privatgebrauch gespeichert und kopiert werden.

Sie dürfen die Dokumente nicht für öffentliche oder kommerzielle Zwecke vervielfältigen, öffentlich ausstellen, öffentlich zugänglich machen, vertreiben oder anderweitig nutzen.

Sofern die Verfasser die Dokumente unter Open-Content-Lizenzen (insbesondere CC-Lizenzen) zur Verfügung gestellt haben sollten, gelten abweichend von diesen Nutzungsbedingungen die in der dort genannten Lizenz gewährten Nutzungsrechte.

# **Terms of use:**

*Documents in EconStor may be saved and copied for your personal and scholarly purposes.*

*You are not to copy documents for public or commercial purposes, to exhibit the documents publicly, to make them publicly available on the internet, or to distribute or otherwise use the documents in public.*

*If the documents have been made available under an Open Content Licence (especially Creative Commons Licences), you may exercise further usage rights as specified in the indicated licence.*



<https://creativecommons.org/licenses/by-nc-nd/4.0/>







Available online at [www.sciencedirect.com](http://www.elsevier.com/locate/egyr)



[Energy Reports 6 \(2020\) 439–446](https://doi.org/10.1016/j.egyr.2019.11.100)



# The 6th International Conference on Power and Energy Systems Engineering (CPESE 2019), September 20–23, 2019, Okinawa, Japan

# Increasing the efficiency of a drone motor by arranging magnetic sheets to windings

Mitsuhide S[a](#page-1-0)to<sup>a,\*</sup>, Masami Nirei<sup>[b](#page-1-2)</sup>, Yuichiro Yamanaka<sup>a</sup>, Tatsuki Suzuki<sup>a</sup>, Yinggang Bu<sup>a</sup>, Tsutomu Mizuno<sup>[a](#page-1-0)</sup>

> <span id="page-1-2"></span><span id="page-1-0"></span><sup>a</sup> *Faculty of Engineering, Shinshu University, 4-17-1 Wakasato, Nagano, 380-8553, Japan* <sup>b</sup> *National Institute of Technology, Nagano College, 716 Tokuma, Nagano, 381-8550, Japan*

> > Received 7 October 2019; accepted 22 November 2019

### Abstract

In recent years, there has been an increase in motorization; therefore, the demand for high-efficiency motors in automobiles and aircrafts will further increase. A drone is an aircraft that flies without a human pilot onboard; it has a short flight time because the size of the mounted battery is limited. The magnetic sheet consists of a composite material with magnetic powder and silicone rubber. The eddy current loss and copper loss of the drone motor reduces when the sheet is attached to the coil. This paper reports on the effect of improving the drone motor efficiency by lowering the leakage magnetic flux of the rotor and increasing the heat dissipation in the simulation and the experiment.

⃝c 2019 Published by Elsevier Ltd. This is an open access article under the CC BY-NC-ND license [\(http://creativecommons.org/licenses/by-nc-nd/4.0/](http://creativecommons.org/licenses/by-nc-nd/4.0/)).

Peer-review under responsibility of the scientific committee of the 6th International Conference on Power and Energy Systems Engineering (CPESE 2019).

*Keywords:* Copper loss; Magnetic composite material; Magnetic sheets; Motor; Stray load loss; Thermal conductivity

# 1. Introduction

Motors have become an essential power source that support modern life [\[2](#page-7-0)]. The ratio of motors to the total industrial power consumption in the world is approximately 35% to 40% [[1\]](#page-7-1). Improving the efficiency of motors is also important from the perspective of preventing global warming [\[7](#page-8-0),[10\]](#page-8-1). In recent years, motorization has increased substantially, and the demand for motors in the automobile and aeronautics industry is expected to increase further. A drone is an aircraft that is remotely controlled using a motor. Drones have a wide variety of applications such as scientific research, aerial photography at disaster sites, and goods transportation. However, drones have a short flight time because their batteries need to be small in size for mounting on the drones. To increase the efficiency of the drone motor, it is important to reduce the power consumption. Motor efficiency can be achieved by increasing the motor size, but a drone motor needs to be compact and high powered for mounting on a drone. To increase the

<span id="page-1-1"></span>Corresponding author. *E-mail address:* [mitsuhide@shinshu-u.ac.jp](mailto:mitsuhide@shinshu-u.ac.jp) (M. Sato).

<https://doi.org/10.1016/j.egyr.2019.11.100>

<sup>2352-4847/© 2019</sup> Published by Elsevier Ltd. This is an open access article under the CC BY-NC-ND license ([http://creativecommons.org/](http://creativecommons.org/licenses/by-nc-nd/4.0/) [licenses/by-nc-nd/4.0/\)](http://creativecommons.org/licenses/by-nc-nd/4.0/).

Peer-review under responsibility of the scientific committee of the 6th International Conference on Power and Energy Systems Engineering (CPESE 2019).

output power, the rated torque and rotational speed of the motor need to be increased. It is desirable to increase the rated rotational speed because an increase in the torque tends to increase the motor size.

The motor loss is classified into copper loss, iron loss, and stray load loss [[11\]](#page-8-2). Studies have shown that coil winding and the use of low-loss core materials are effective in reducing the copper loss and the iron loss [[8](#page-8-3)[,9](#page-8-4)]. However, there are few reports on the eddy current losses for the winding, which accounts for most of the stray load loss. The eddy current loss generated in the winding depends on the fundamental frequency of the excitation current and the carrier frequency of the pulse width modulation inverter. The drone motor has high fundamental and carrier frequency because it has to be small in size with a high output. The influence of the eddy current loss generated in the winding becomes large [[4](#page-7-2)[,5](#page-7-3)]. Furthermore, the conductor resistivity increases with the temperature rise of the coil during operation. Therefore, it is effective to increase the heat dissipation of the armature and to lower the armature resistance to increase the efficiency.

Therefore, we considered placing a magnetic sheet on the winding to reduce the eddy current loss and the copper loss of the drone motor. The magnetic sheet consisted of a composite material with magnetic powder and silicone rubber. The loss improvement effect by controlling the magnetic flux was reported on a converter or a power transmission coil [[3,](#page-7-4)[6](#page-7-5)]. Therefore, we proposed to reduce the eddy current loss caused by the leakage flux on the field side being linked to the winding by arranging a magnetic sheet on the winding. Furthermore, the magnetic sheet had high thermal conductivity; therefore, the heat dissipation of the winding could be improved and the increase in electrical resistance could be suppressed. This paper reports the results of simulations and experiments on the effect of the placement of the magnetic sheet on the windings to increase the efficiency of the drone motor.

# 2. Structure

#### <span id="page-2-1"></span>*2.1. Drone motor*

[Fig.](#page-2-0) [1](#page-2-0) shows the structure of the drone motor. The drone motor is an outer rotor type, and its rated output was 318 W. There were 14 poles and 12 slots. The stator height excluding the coil end was 13 mm; the stator outer diameter was 48 mm. The outer diameter of the mover was 57.3 mm, and the gap length was 0.3 mm. The coil was a concentrated winding with a round wire. The rotor was the surface permanent magnet type.



Fig. 1. Structure of the drone motor (unit: mm).

#### <span id="page-2-0"></span>*2.2. Magnetic sheets*

The magnetic sheet was produced by mixing a magnetic powder and two-component silicone rubber; then, the material was baked and stretched thinly. Two effects are expected by sticking the magnetic sheet to the winding. First, the magnetic powder contained in the magnetic sheet prevented interlinking with the winding by controlling the path of the leakage flux from the rotor. This helps to reduce the current density bias and the eddy current losses of the windings. Second, the magnetic sheet had high heat conductivity; therefore, this improved the heat dissipation of the winding. We expected to decrease the electrical resistance by suppressing the temperature rise during energization.

In Section [3,](#page-3-0) we confirm the efficiency improvement effect that accompanies the reduction of eddy current losses by pasting a magnetic sheet in the simulation. In Section [4,](#page-4-0) we confirm the improvement in efficiency associated with the improvement in the heat dissipation of the winding and the reduction of the eddy current loss in the experiment.

# 3. Simulation

# <span id="page-3-0"></span>*3.1. Simulation conditions*

[Fig.](#page-3-1) [2](#page-3-1) shows the analysis model of the drone motor with the magnetic sheet. The magnetic sheet is placed at the outer periphery of the winding. This helps to prevent leakage flux from the rotor that has entered the slot from being linked to the winding. Also, the eddy current loss in the winding can be reduced. [Table](#page-3-2) [1](#page-3-2) shows the analysis conditions. The windings of the analytical model use the conductor specifications to determine the current density distribution. For obtaining the resistance, inductance, copper loss, torque, and iron loss in this simulation, we used two-dimensional magnetic field transient analysis of JMAG-Designer. The fundamental frequency of the excitation current was 933 Hz because there were 14 poles, and the rotational speed of the rotor was 8000 rpm. The thickness of the magnetic sheet was 0.1 mm.



Fig. 2. Analysis model of the drone motor with magnetic sheet.

Item	Contents
Software	JMAG-Designer $(x64)$ Ver.17.0
Analysis	Two-dimensional magnetic field analysis
Solution	<b>FEM</b>
	Copper: 1/10 or less of the skin depth,
Mesh size	Magnetic layer : 10 mm,
	Air: Automatic
Analysis area	Analysis in 10 times the analysis model
Rotor speed	$N_{\rm r} = 8000$ rpm
Current	$I = 30$ A <sub>max</sub>
	Copper : $(r = 1.72 \times 10^{-8} \text{ W m}, m_r' = 1, m_r'' = 0)$
Material	Magnetic composite material : $(m_r' = 20, m_r'' = 0)$
	Air: $(r = \infty$ W m, $m_r' = 1$ , $m_r'' = 0$ )

<span id="page-3-2"></span><span id="page-3-1"></span>Table 1. Simulation conditions.

## *3.2. Simulation results*

[Fig.](#page-4-1) [3](#page-4-1) shows the magnetic flux lines and current density distribution. The magnetic flux partially leaked when the mover linked to the winding was reduced by disposing the magnetic sheet. The bias of the current density was slightly reduced because the flux linkage to the winding was reduced. The analysis results are shown in [Table](#page-4-2) [2.](#page-4-2) The electrical resistance with the magnetic sheet was reduced by 3.2% because of the reduced current density bias. The copper loss with the magnetic sheet was reduced by 1.8%. Furthermore, the iron loss and the torque were almost unchanged, and there was almost no adverse effect of sticking the magnetic sheet. The efficiency improved by 0.2% because of the reduction of copper loss. Eddy current losses due to wire interlinkage will be larger in more high-speed motors or open slot motors because they have larger skin effects and proximity effects, and there is large leakage flux from the mover. In such cases, the efficiency improvement because of the magnetic sheet is further enhanced.



Fig. 3. Flux line and distribution of current density.

<span id="page-4-2"></span><span id="page-4-1"></span>



# 4. Experiment with magnetic sheet

#### <span id="page-4-0"></span>*4.1. Experimental configuration*

[Fig.](#page-5-0) [4\(](#page-5-0)a) shows the overall experimental structure. The drone motor, torque meter, and load motor are connected on the same shaft via a coupling (see [Fig.](#page-5-0) [4\(](#page-5-0)b)). The power supply was a drone battery. The speed of the drone motor was controlled by inputting a pulse wave using a function generator. A coreless brushless DC motor was used as the load motor, and the regenerative energy was consumed by the electronic load. The electronic load was used in the constant resistance mode, and the resistance was adjusted to achieve the desired torque.

The magnetic sheet was prepared according to the procedure shown in [Fig.](#page-5-1) [5.](#page-5-1) The raw material for the magnetic composite material was manufactured in steps by mixing amorphous 1 (particle size 2.6 µm), amorphous 2 (particle size 10  $\mu$ m), and silicone rubber in the ratio of 5: 1.5: 1.49 by vacuum stirring. The magnetic composite material is dropped on a polyethylene terephthalate (PET) sheet, and the air bubbles were removed by a shaker. The vacuum evacuation is performed using a vacuum desiccator. Again, it was vibrated by a shaker to remove all air bubbles. The PET sheet was sandwiched and pressurized to the desired thickness. The magnetic sheet was completed by baking with the PET sheet. The complex permeability was measured using an impedance analyzer (16454A) and a terminal adaptor (42942A) and was found to be  $\mu' = 19.4$ ,  $\mu'' = 0.25$ . These values were close to the characteristics used in the simulation. [Fig.](#page-6-0) [6](#page-6-0) shows the stator of a drone motor with magnetic sheets. A two-component acrylic adhesive was used to attach the magnetic sheet to the winding of the motor.



Fig. 4. Experiment configuration.

<span id="page-5-0"></span>

Fig. 5. Production of magnetic sheets.

# <span id="page-5-1"></span>*4.2. Results*

The motor was driven at the maximum rotational speed with the electronic load set to 1  $\Omega$  for the rotation resistance. Measurements start after reaching the maximum rotational speed. [Fig.](#page-6-1) [7](#page-6-1) is the temperature distribution by the thermo shot for the highest winding temperature. [Fig.](#page-6-1) [7\(](#page-6-1)a) and (b) show the case without and with the magnetic sheet, respectively. The temperature of the winding in both cases reached the maximum approximately



Fig. 6. Drone motor with magnetic sheets.

<span id="page-6-0"></span>

Fig. 7. Temperature distribution of drone motor 9 min after the start of operation.

<span id="page-6-1"></span>9 min after starting the measurement. The maximum temperatures without and with the magnetic sheets were 60.8 ◦C and 59.4 ◦C, respectively; these temperatures were maintained during the operation. The temperature rise was suppressed by using the magnetic sheet. [Fig.](#page-7-6) [8](#page-7-6) shows the time transition of the measurement result. Fig. 8(a) shows the graph for the rotational speed. The rotational speed was the same for approximately 16 min, but the rotational speed without the magnetic sheet decreased with the passage of time. The rotational speed could not be maintained because the battery capacity had dropped. [Fig.](#page-7-6) [8\(](#page-7-6)b) shows the torque. There was no change in the torque because of the magnetic sheet. The torque without the magnetic sheet dropped sharply after 16 min because of a decrease in battery capacity. The electrical resistance with the magnetic sheet was reduced by  $2.6\%$  (see [Fig.](#page-7-6) [8](#page-7-6)(c)). This happened because of two reasons: the reduction of eddy current loss in the winding and the suppression of temperature rise due to the high thermal conductivity of the magnetic sheet. From the simulation results, we can see that the latter effect is large, as described in Section [2](#page-2-1).

[Fig.](#page-7-7) [9](#page-7-7) shows the efficiency of the motor. The efficiency is the ratio of input to output. The input power of the motor is measured by a power meter, and the output is the product of the torque and rotational speed. With the magnetic sheet, the maximum efficiency was improved by 1.5%. To improve efficiency, it is useful to stick the sheet to the winding. Furthermore, if the magnetic sheet can be stuck to the deepest part of the slot, the heat radiation effect and the efficiency improvement effect can be enhanced.

## 5. Conclusion

A magnetic sheet was placed around the winding to increase the efficiency of the drone motor. In the magnetic field analysis simulation, the increase in electrical resistance was suppressed so that the flux of the rotor interlinks

<span id="page-7-6"></span>

Fig. 9. Motor efficiency.

<span id="page-7-7"></span>with the winding by using the magnetic sheet. The electrical resistance was reduced, and the efficiency was improved by 0.2%. In addition, we could improve the heat dissipation of the winding because of the high thermal conductivity of the magnetic sheet. In the experiments that use a drone motor, the increase in electrical resistance was suppressed, and the maximum efficiency was improved by 1.5%. Our results prove that the pasting of the magnetic sheet was effective for improving the motor efficiency.

# Acknowledgments

This work was partially supported by Tsugawa Foundation. We received generous support from Hiroaki Usui and Katsutoshi Mizoguchi of Shinano Kenshi Co., Ltd., Japan

# References

- <span id="page-7-1"></span>[1] [de Almeida Aníbal T, Ferreira Fernando JTE, Baoming Ge. Beyond induction motors—Technology trends to move up efficiency. IEEE](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb1) [Trans. Ind. Appl. 2014;50\(3\):2103–14.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb1)
- <span id="page-7-0"></span>[2] [Dorrell DG, Knight AM, Popescu M. Performance improvement in high-performance brushless rare-earth magnet motors for hybrid](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb2) [vehicles by use of high flux-density steel. IEEE Trans. Magn. 2011;47\(10\):3016–9.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb2)
- <span id="page-7-4"></span>[3] Endo S, Bu Y, Mizuno T. 2018. Weight reduction and high efficiency of wireless power transmission coil using magnetocoated aluminum plate. In: Proc. EVS 31 & EVTeC 2018, No.C1-3, pp. 1-6.
- <span id="page-7-2"></span>[4] [Ishak D, Zhu ZQ, Howe D. Eddy-current loss in the rotor magnets of permanent-magnet brushless machines having a fractional number](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb4) [of slots per pole. IEEE Trans. Magn. 2005;41\(9\):2462–9.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb4)
- <span id="page-7-3"></span>[5] [Iwasaki S, Deodhar RP, Liu Y, Pride A, Zhu ZQ, Bremner JJ. Influence of PWM on the proximity loss in permanent-magnet brushless](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb5) [AC machines. IEEE Trans. Ind. Appl. 2009;45\(4\):1359–67.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb5)
- <span id="page-7-5"></span>[6] [Konno Y, Yamamoto T, Kawahara S, Torishima K, Bu Y, Mizuno T. Examination of high Q factor inductor with vacant space for a](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb6) [non-isolated DC–DC converter. IEEE Trans. Magn. 2018;54\(11\). 8401504.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb6)
- <span id="page-8-0"></span>[7] [Lu S. A review of high-efficiency motors: Specification, policy, and technology. Renew. Sustain. Energy Rev. 2016;59:1–12.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb7)
- <span id="page-8-3"></span>[8] [Makita S, Takahashi E, Nashiki M, Doki S. New motor having a simple structure with three-dimensional magnetic circuit and loop](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb8) [windings. IEEJ Trans. Ind. Appl. 2014;134\(3\):363–9.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb8)
- <span id="page-8-4"></span>[9] [Ohta M, Yoshizawa Y. Improvement of soft magnetic properties in \(Fe0:85B0:15\)100-xCux melt-spun alloys. Mater. Trans.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb9) [2007;48\(9\):2378–80.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb9)
- <span id="page-8-1"></span>[10] [Trianni A, Cagno E, Accordini D. A review of energy efficiency measures within electric motors systems. Energy Procedia](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb10) [2019;158:3346–51.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb10)
- <span id="page-8-2"></span>[11] [Yamazaki K, Watanabe Y. Stray load loss Calculation of induction motors using electromagnetic field analysis. IEEJ Trans. Ind. Appl.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb11) [2008;128\(1\):56–63.](http://refhub.elsevier.com/S2352-4847(19)30919-9/sb11)